FM BROADCAST TRANSMITTER

Type: XFT-614 digital

new!



AVEC ALIMENTATION ELECTRONIQUE SPÉCIAL POUR DES RÉSEAUX INSTABIL DE 140 à 245 Vac 50-60Hz SORTI CASQUE - HEADPHONE : CONTROLE MPX + AUDIO SOFT LIMITTER SYSTEM CONTROLE AUDIO LEVEL

XFT-614 LCD SCREEN MODULAR SYSTEM

SORTI MONITOR: MPX + AUDIO

PLUG IN 'S: - DIGITAL + ANALOGUE XLR

- MONO DOUBLE XLR - RDS + LOGICIEL - MP3 AUDIO PAR USB

SCREEN CONTROLL: - TEMPERATURE

- PUISSANCE DE SORTI ET RETOUR- CONTROLE DEVIATION + AUDIO + MPX

- CONTROLE ALIMENTATIONS

NAVIGATEUR - FREQUENCY

- PUISSANCE - POWER

- DEVIATION

- PASS WORD - LANGUAGE

<u>DIGITAL OPTIONS</u>: - USB interupt check list

- RS485

PROTECTIONS - POWER + SWR + TEMPERATURE

impedance 50 Ohm 87,5 - 108freq band 10 Khz freq step up/down modulation FΜ SET BY DELIVERY 75 Khz modulation deviation mpx connector **BNC** impedance 10K Ohm O dB - 775mV-2,2Vpp level distortion 0,05% 1Khz&100%modulation type ST09 modulateur AC power input 140-245 V AC AC connector type EURO AC switch **DP ON FRONT** Fuse 4 Amp -F (32) 100 / 900 Watt max AC Power IN alimentation 48v 1x APR48-G3 1800W 1X PSU-100 alimentation +12v préampli BG **UNIT 1X600w** ampli Ambient temp 10 - 30°c (32 - 113°f) cooling 1x DC forced air-ball bears 120x120 temp protection protect by 70° c inside 19 inch 4U D: 360mm Housing Weight 18Kg approx Panel size 482 x 172

made in belgium

connector out

Tel 0032-57-218828 Fax 0032-57-218759 email : mediamat@skynet.be Mediamat broadcast services Groenestraat 12 8900 IEPER BELGIUM



