

# KAJ INSTALLATIONS & SERVICES

## BOLLINGER MICRO 126

### HOW TO ADD A NEW REMOTE TO YOUR GATE RECEIVER

1. You will need a remote control that operates your gate
2. Take the existing remote and new remote and stand close to the gate motor
3. Turn the remote that works over and find the small button (recessed) on the rear
4. Press the small button using a ballpoint pen or similar
5. The receiver will emit a "beep"
6. Press the button on the front of the new remote control. The receiver will "beep"
7. If there are more than one remote to add, press the front button on all of the remotes to be coded. There is only approximately 10 seconds available from each entry, to press the next button
8. After 10 seconds the unit will beep twice indicating end of programming. Test the remotes that have been added for successful operation of the gate

The instructions above are for the products illustrated below:



If the instructions provided do not work the gate receiver may have a different capacity memory. The memory capacity determines how many remotes can be added or may relate to a commercial / group property receiver.

If this happens please contact us either as a request through our website or contact direct. Contact details are available on this website.



Unit 2, 4 Beam Road  
PO Box 2303  
MANDURAH WA 6210

PHONE 0404 058 779  
FAX (08) 9583 5874  
EMAIL [KAJ.Install2@westnet.com.au](mailto:KAJ.Install2@westnet.com.au)  
WEBSITE [www.kajinstallations.com](http://www.kajinstallations.com)